

APL2400-200

UltraSpeed™ CoaxLine™ Quad Ethernet NetBridge™

User's Manual



Version 1.3

IMPORTANT SAFETY INSTRUCTIONS

1. Please read all instructions before installing and operating APL2400-200 and keep all instructions for later reference.
2. Please follow all warnings and instructions marked on the product.
3. **Unplug the AC coupler from the wall outlet before cleaning. Use a damp cloth for cleaning. DO NOT use liquid cleaners or aerosol cleaners.**
4. **DO NOT** operate APL2400-200 near water.
5. APL2400-200 should **never** be placed near or over a radiator, or heat register.
6. APL2400-200 relies on the building's electrical installation for short-circuit (over current) protection.
7. Ensure that a fuse or circuit breaker **no larger than 120 VAC 15A or 240 VAC 6A** is used on the phase conductors (all current-carrying conductors).
8. **DO NOT** allow anything to rest on the APL2400-200 interconnect cables. **DO NOT** locate APL2400-200 where people may walk on the cables.
9. APL2400-200 has its own power filter for protection against surges.
10. **APL2400-200 is NOT field serviceable and should not be opened under any circumstance.** Opening or removing covers may result in exposure to dangerous voltage points or other risks.
11. Unplug the AC coupler from the wall outlet and refer the product to qualified service personnel for the following conditions:
 - When the interconnect cords are damaged or frayed.
 - If liquid has been spilled into the product.
 - If the product has been exposed to rain or water.
 - If the product does not operate normally when the operating instructions are followed.
 - If the product exhibits a distinct change in performance.

Copyright © 2009 by Aboundi Inc. All rights reserved.

No part of this documentation may be reproduced in any form or by any means or used to make any derivative work (such as translation, transformation, or adaptation) without written permission from the copyright owner.

All the other trademarks and registered trademarks are the property of their respective owners.

Statement of Conditions

The content described in this manual may be improved or changed at any time and it is subject to be changed without notice.

Manufacturer assumes no responsibility for errors contained herein or for direct, indirect, special, incidental or consequential damages with the furnishing, performance, or use of this manual or equipment supplied with it, even if manufacturer or its suppliers have been advised of the possibility of such damages.

Electronic Emission Notices

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference.
- (2) This device will accept any interference received, including interference that may cause undesired operation.

Table of Content

1.	Introduction	5
1.1.	Features	5
1.2.	Product Kit	6
1.3.	LED.....	6
1.4.	Hardware Installation.....	7
1.5.	Application	8
2.	Software Installation	9
2.1.	System Requirements.....	9
2.2.	Installation	9
3.	Web Configuration.....	12
3.1.	Start-up and Log in	12
3.2.	Connection Info	13
3.3.	Configuration.....	14
3.3.1.	Security Page	15
3.3.2.	Network Page	16
3.3.3.	VLAN Page	17
3.3.4.	QoS Page	18
3.4.	Change Password.....	19
3.5.	Firmware Upgrade	20
3.6.	Factory Reset	21
3.7.	Reboot	22
4.	Default Settings	22

1. Introduction

The Aboundi APL2400-200 UltraSpeed™ CoaxLine™ Quad Ethernet NetBridge™ allows utilizing the coaxial cable lines already deployed in a building as the network infrastructure connections. The APL2400-200 provides reliable network quality and enables IP Cameras, Video Servers, POS, Media Converters, Printers, Digital Signages and Network Equipments for easy broadband access in a tight cluster space.

The APL2400-200 NetBridge™ can be quickly installed for commercial applications require high bandwidth and critical demand of reliable network connection (QOS). This networking group can be easily reallocated without the need to rewire “home run” Ethernet drops to such cluster group locations.

The APL2400-200 NetBridge™ is designed specifically for small cluster networking applications by providing four MDI/MDIX auto detection RJ-45 ports that can connect to any 10/100Mbps Ethernet ports on the computer and other peripheral devices. The network over the coaxial cables can convert to the existing power line with ACX1000 VersatileWire™ Adaptor to work with all Aboundi UltraSpeed™ series NetBridge™. This capacity provides the flexibility to enhance your network to be ubiquitous to everywhere in the building.

1.1. Features

- Four shielded RJ-45 MDI/MDIX auto detection Ethernet Ports
- Up to 200Mbps speed over the existing coaxial cables
- Integrated Quality of Service (QOS) allows reliable triple play applications
- Reliable and cost effective network
- Supports up to sixteen APL2400-200 devices on one network domain
- 168-bit Tri-DES encryption for secure data transmission
- Network segmentation through network identifier
- Ident-and-Connect™ feature allows ease of network scan and network segmentation
- Web based configuration
- Up to 2.5 KM of operational distance
- Compliance with IEEE802.3 10BASE-T, IEEE802.3u 100BASE-TX , UPA
- Fully compatible with Aboundi UltraSpeed™ series PowerLine NetBridge™

1.2. Product Kit


Before starting installation, please make sure the APL2400-200 package includes the following five items:

- 1) Quick Installation Guide
- 2) APL2400-200 unit
- 3) CD-ROM (containing Ultra NetBridge™ Utility for Windows and User's Manual).
- 4) Cat 5e cable
- 5) Power cord
- 6) BNC to F adaptor




If anything from the above items is missing, please contact your vendor.

1.3. LED

The following figure shows the APL2400-200 LED indicator.



The function for each LED is described as follow:

- | | | |
|---|-----------------------|---|
|  | PWR-Green: | On when the power is on. |
|  | LNK/ACT-Blue: | On when PowerLine Link speed over 12Mbps, |
| | Purple: | On when PowerLine Link speed between 12Mbps and 6 Mbps, |
| | Amber: | On when PowerLine Link speed under 6Mbps, |
| | | Blinking when PowerLine activity is detected. |
|  | LNK/ACT-Green: | On when Ethernet link is detected; |
| | | Blinking when Ethernet Activity is detected |

1.4. Hardware Installation

- Step 1 Plug the included Ethernet network cable into the computer's Ethernet port.



- Step 2 Plug the other end of this cable into the Ethernet port of the APL2400-200.



- Step 3 Plug the power cord into the electrical port of APL2400-200



- Step 4 Connect the coaxial cable with F-type male connector.



- Step 5 Plug the power plug into the AC socket on the wall.




1.5. Application

Example – CCTV Application

APL2400-200 enables to extend the new IP Camera to run over the existing long distance coaxial cable infrastructure and the extension of the ubiquitous Ethernet applications through coaxial cable deployment already in existence. APL2400-200 also turns any existing analog video cable into a high-speed Ethernet connection. This allows multiple network cameras to replace a single analog CCTV camera without installing any new cable. Additionally, you'll extend the coverage of the surveillance system by simply branching the cabling with coaxial cable splitters.

- Innovative - Up to 200Mbps speed over existing coaxial cables
- Adaptive - No RF interference to the network
- Extensive - At least 2000 meters connection range



2. Software Installation

Please follow the steps described in this section to install your Ultra NetBridge™ Utility.

2.1. System Requirements

Before installing Ultra NetBridge™ Utility, make sure the PC meets these requirements for hardware installation:


- Microsoft Windows* 98SE, ME, 2000, XP or Vista
- Pentium® 166 MHz processor, equivalent or higher
- One free Ethernet port for UltraSpeed™ Series PowerLine NetBridge™
- 30M free disk space

Only supported network components are installed:


- Network Clients: Client for Microsoft Networks, Client for Netware Networks
- Network services: File and print sharing for Microsoft Networks
- Network protocols: Microsoft's TCP/IP, IPX/SPX, NetBEUI, or Net BIOS support for IPX/SPX

2.2. Installation


Before the installation, please close the application (if an older version is running) and uninstall it. To install the application just run the setup executable program **Setup.exe** in the Product CD-ROM, and follow the steps of the installation wizard. To start the Ultra NetBridge™ Utility installation, press “**Next>**”:




Next screen allows you to select the installation folder for the application. Click “**Next>**” to start the installation:




Please wait for Installation progress bar finish. Press “**Cancel**” button to abort the installation process.



Utility has been installed. Press **“Finish”** to start the application:



Run the Utility

After installed the utility, please run the utility from Start / Programs or double-click the Ultra NetBridge™ Utility icon  as shown in Figure 2.2. There is utility user guide which has installed at same place. Please use adobe reader to open and read it for detail of the software.




Figure 2.2 Ultra NetBridge™ Utility

3. Web Configuration

The APL2400-200 UltraSpeed™ NetBridge™ provides Web based configuration by your PC Web browser, such as Microsoft Internet Explorer. This approach can be adopted in any MS Windows, Mac or UNIX based platforms. You can configure the NetBridge™'s IP address using the Ultra Netbridge™ Utility before they use the Web Configuration.

3.1. Start-up and Log in

Activate your browser, enter the IP address of NetBridge™ in the **Location** (for Netscape) or **Address** (for IE) field and press ENTER. For example: **http://192.168.1.176**.

After the connection is established, you will see the web user interface of NetBridge™. At the **Password** field, enter the password (the factory default value is **admin**) and then click **Log in**




Figure 3.1.1 User Main Menu

If the password is correct, the web appearance will be changed as shown in Figure 3.1.2. As listed in its **Connection Info** page, there are several options for system administration.




Figure 3.1.2 Connection Info Page

3.2. Connection Info

The Connection Info page displays basic Information about the NetBridge™

- General Information:** MAC and IP addresses and the number of boots.
- Available Connections:** Display the list of all NetBridge™ devices discovered on the current logical power line or coax networks and the connectivity status.

3.3. Configuration

The Configuration page displays the current settings of the NetBridge™ including Security, Network, VLAN, QoS, System Information.

The screenshot shows the PowerLine NetBridge™ web interface in a Mozilla Firefox browser window. The address bar shows <http://192.168.1.176/>. The page title is "PowerLine NetBridge™" and the version is "NetBridge FW v1.0".

Admin Main Menu

- Connection Info Configuration
 - Security
 - Network
 - VLAN
 - QOS
- Change Password
- Firmware Upgrade
- Factory Reset
- Reboot

[Log out](#)

Security Status

Item	Value
▶ Network Identifier	Electric-Connect
▶ Encryption Key	Disabled
▶ Node Type	Client

Network Status

Item	Value
▶ MAC Address	0004DB0155C0
▶ IP Configuration	DHCP
▶ IP Address	192.168.1.176
▶ Subnet Mask	255.255.255.0
▶ Default Gateway IP Address	192.168.1.1

VLAN Status

Item	Value
▶ VLAN Configuration	Disabled
▶ VLAN Tag	0

<http://192.168.1.176/info.htm>

Figure 3.3 Connection Info Page

3.3.1. Security Page

The Security page enables you to modify the Network Identifier, Encryption Key and the Mac mode. displays the current settings of the NetBridge™ including Security, Network, VLAN, QoS and System Information.




Figure 3.3.1 Security Page

3.3.2. Network Page

The Network page enables you to modify the network settings of the NetBridge™.




Figure 3.3.2 Network Page

3.3.3. VLAN Page

The VLAN page enables you to modify the VLAN configuration of the NetBridge™.




Figure 3.3.3 VLAN Page

3.3.4. QoS Page

The QoS page enables you to modify the QoS configuration of the NetBridge™.




Figure 3.3.4 QoS Page

3.4. Change Password

You can change the administration password for the NetBridge™ in the Change Password page.




Figure 3.4 Change Password Page

3.5. Firmware Upgrade

You can upgrade the firmware for the NetBridge™ in the Firmware Upgrade page.




Figure 3.5 Firmware Upgrade Page

3.6. Factory Reset

You can reset the NetBridge™ to the factory default settings from the Factory Reset page.




Figure 3.6 Factory Reset Page

3.7. Reboot

You can reboot the NetBridge™ remotely from the Reboot page.




Figure 3.7 Reboot Page

4. Default Settings

Administration Password: **admin**

IP Address: **0.0.0.0**

Network Identifier: **Electric-Connect**

Mac Node: **Client**